



Tech Info Library

Apple Modem 300/1200: Configuring it with the Apple IIe

Revised: 3/3/86
Security: Everyone

Apple Modem 300/1200: Configuring it with the Apple IIe

=====

I. Switch settings

A. For 300 baud:

1. Super Serial Card:

		1	2	3	4	5	6	7			1	2	3	4	5	6	7	
	ON	X			X	X	X	X		ON	X		X	X		X		
SW1										SW2								
	OFF		X	X						OFF		X			X		X	
			1	2	3	4	5	6	7			1	2	3	4	5	6	7

-- Jumper Block to MODEM

2. Modem:

UP				X
DOWN	X			
	1	2	3	
	CD	BC	DTR	

-- Switch 2 can be up or down; it isn't used.

B. For 1200 baud:

1. Super Serial Card:

		1	2	3	4	5	6	7			1	2	3	4	5	6	7	
	ON		X	X	X	X	X	X		ON	X		X	X		X		
SW1										SW2								
	OFF	X								OFF		X			X		X	
			1	2	3	4	5	6	7			1	2	3	4	5	6	7

-- Jumper Block to MODEM

2. Modem:

UP		X	X
DOWN	X		
	1	2	3
	CD	BC	DTR

II. Connection:

A. Cable IIe: Apple Service Part Number 590-0121

Super Serial	Apple
Interface Card	Modem 300/1200
DB-25	DB-9
1	8
2	9
3	5
6	2
7	3
8,5	7
20	6

Apple Technical Communications

Tech Info Library Article Number:1773